

Sigtronics Digital Voice Recorder

Installation and Operating Instructions



Digital Voice Recorder Features

Instant Record and Playback feature. Records 60 seconds of information from dispatch to be played back later, which helps to reduce radio traffic. Both sides of radio and intercom conversations can be recorded. The recorder is non-volatile, messages will not erase with loss of power. Messages erase only when recorded over. The recorder is compatible with all Sigtronics Intercom systems.

Installation

Attach the voice recorder in a convenient location using the adhesive mounting strips. Connect the wiring harness color-for-color to the Sigtronics intercom wiring. See table below and diagram on page 2.

Connector Pinout

Pin	Wire Color	Function	Connect To
1	Red	Power Input	Vehicle Power +12 V DC
2	Green	Power Ground	To Chassis Ground
3	Blue	Output to Intercom	Intercom Headphone Bus
4	Black	Output to Intercom	Intercom Common Return Line (Black)

Operating Instructions

RECORD – with your headsets on and intercom working, press and release the RECORD button. The Red RECORD LED will come on. Anything being heard in the headphones (incoming or outgoing radio traffic, or anyone speaking on intercom) will be recorded. Press the STOP/PLAY button momentarily to stop recording. The RECORD LED will turn off. The recorded message will remain in memory whether or not power is connected.

PLAYBACK – Press the STOP/PLAY button momentarily. The Green PLAY LED will come on and playback of your recorded message will start. Playback will continue until the end of the recorded message, and stop automatically. Pressing the STOP/PLAY button again during playback will STOP playback. When playback is stopped the PLAY LED will turn off.

Warranty: One year parts and labor.

Standard Equipment Included

Part Description	Part Number	Quantity
Interface Cable	N/A	1
Foam, Double Sided	100720	2



Made in the U.S.A.

Specialists in "SOUND" Management

178 East Arrow Highway, San Dimas, CA 91773 (909) 305-9399

